

Amendments to the Specification

Please replace the title as follows:

~~ELECTRONIC CIRCUIT, DRIVING METHOD FOR ELECTRONIC CIRCUIT, SYSTEM~~
~~AND METHODS FOR DRIVING AN ELECTRO-OPTICAL DEVICE, DRIVING~~
~~METHOD FOR ELECTRO-OPTICAL DEVICE, AND ELECTRONIC APPARATUS~~

Attached are a marked-up copy of the originally filed specification and a clean substitute specification in accordance with 37 C.F.R. §§1.121(b)(3) and 1.125(c). The substitute specification contains no new matter.

Please replace the Abstract with the attached amended Abstract.

Amendments to the Claims:

The following listing of claims will replace all prior versions, and listings, of claims in the application:

1. (Currently Amended) An electronic ~~circuit characterized by~~circuit, comprising:
 - a first transistor including a first terminal, a second terminal, and a first control terminal;
 - a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being ~~connected~~coupled to the first control terminal;
 - a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~coupled to the first control terminal; and
 - a third transistor including a fifth terminal and a sixth terminal, the fifth terminal being ~~connected~~coupled to the second electrode, the second control terminal being ~~connected~~coupled to the third terminal.
2. (Currently Amended) ~~An~~The electronic circuit according to Claim 1,
_____further comprising a fourth transistor including a seventh terminal and an eighth terminal, the seventh terminal being ~~connected~~coupled to the fourth terminal.
3. (Currently Amended) ~~An~~The electronic circuit according to Claim 1,
_____the first terminal being ~~connected~~coupled to an electronic element.
4. (Currently Amended) ~~An~~The electronic circuit according to Claim 3,
_____the electronic element being a current-driven element.
5. (Currently Amended) An electronic ~~circuit comprising~~circuit, comprising:
 - a plurality of first signal lines;
 - a plurality of power lines; and

a plurality of unit circuits, each of the plurality of unit circuits further
comprising:

a first transistor including a first terminal, a second terminal, and a first control terminal;

a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being ~~connected~~ coupled to the first control terminal;

a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~ coupled to the first control terminal; and

a third transistor including a fifth terminal, a sixth terminal, and a third control terminal, the fifth terminal being ~~connected~~ coupled to the second electrode,

the second control terminal being ~~connected~~ coupled to the third terminal, and

the third control terminal being ~~connected~~ coupled to a respective first signal line of the plurality of first signal lines.

6. (Currently Amended) ~~An~~ The electronic circuit according to Claim 5, further comprising a plurality of second signal lines, each of the plurality of unit circuits further comprising a fourth transistor including a seventh terminal, an eighth terminal, and a fourth control terminal,

the seventh terminal being ~~connected~~ coupled to the fourth terminal, and the fourth control terminal being ~~connected~~ coupled to a respective second signal line of the plurality of second signal lines.

7. (Currently Amended) ~~An~~ The electronic circuit according to Claim 5, the first terminal being ~~connected~~ coupled to an electronic element.

8. (Currently Amended) ~~An~~ The electronic circuit according to Claim 7,

the electronic element being a current-driven element.

9. (Currently Amended) An electronic ~~circuit comprising~~circuit, comprising:
a holding element ~~for holding~~that holds a signal as a charge;
a first switching transistor ~~for controlling~~that controls the transfer of the signal to the holding element;
a driving transistor of which ~~the~~a conduction state is set according to the charge held by the holding element; and
an adjustment transistor ~~for setting~~that sets a control terminal of the driving transistor to a predetermined potential prior to the transfer of the signal to the holding element.

10. (Currently Amended) ~~An~~The electronic circuit according to Claim 9,
_____ ~~further comprising~~ a second switching transistor ~~for controlling~~that controls the electronic connection or the electronic disconnection between the adjustment transistor and the predetermined potential.

11. (Currently Amended) ~~An~~The electronic circuit according to Claim 9,
the driving transistor being ~~connected~~coupled to an electronic element.

12. (Currently Amended) ~~An~~The electronic circuit according to Claim 11,
the electronic element being a current-driven element.

13. (Currently Amended) A driving method for an electronic circuit comprising:
a first transistor including a first terminal, a second terminal, and a first control terminal;
a second transistor including a third terminal and a fourth terminal, the third terminal being ~~connected~~coupled to the first control terminal; and
a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~coupled to the first control terminal,

the driving method comprising:

~~a first step of~~ electronically connecting the fourth terminal to a predetermined potential for setting the first control terminal to a first potential; and

~~a second step of,~~ when the fourth terminal is electronically disconnected from the predetermined potential, changing the potential of the second electrode of the capacitive element from a second potential to a third potential to change the potential of the first control terminal from the first potential.

14. (Currently Amended) ~~A~~ The driving method for the electronic circuit according to Claim 13,

the potential of the second electrode being set to the second potential while at least the ~~first step~~ fourth terminal is electronically connected to a predetermined potential is being performed.

15. (Currently Amended) ~~An electro-optical device comprising device,~~
comprising:

a plurality of scanning lines;

a plurality of data lines;

a plurality of power lines; and

a plurality of unit circuits having electro-optical elements,

~~the electro-optical device characterized in that~~ each of the plurality of unit circuits further comprises:

a first transistor including a first terminal, a second terminal, and a first control terminal;

an electro-optical element ~~connected~~ coupled to the first terminal;

a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being ~~connected~~ coupled to the first control terminal;

a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~ coupled to the first control terminal;

a third transistor including a fifth terminal, a sixth terminal, and a third control terminal, the fifth terminal being ~~connected~~ coupled to the second electrode; and

a fourth transistor including a seventh terminal and an eighth terminal, the seventh terminal being ~~connected~~ coupled to the fourth terminal,

the second control terminal is ~~connected~~ coupled to the third terminal,

the third control terminal is ~~connected~~ coupled to one of the plurality of scanning lines, and

the sixth terminal is ~~connected~~ coupled to one of the plurality of data lines.

16. (Currently Amended) ~~An~~ The electro-optical device according to Claim 15,
~~characterized in that the electro-optical element is being~~ an organic EL element.

17. (Currently Amended) An electro-optical device comprising a plurality of scanning lines, a plurality of data lines, a plurality of power lines, and a plurality of unit circuits having electro-optical elements,
~~the electro-optical device characterized in that~~ each of the plurality of unit circuits comprises:

a first switching transistor of which the conduction state is controlled according to a scanning signal sent through one corresponding scanning line of the plurality of scanning lines;

a holding element ~~for accumulating~~ that accumulates a data signal sent through one data line of the plurality of data lines and the first switching transistor, as a charge;

a driving transistor of which the continuity state is set according to the amount of the charge accumulated by the holding element, ~~for supplying~~that supplies current having a current level according to ~~the~~a conduction state to the electro-optical elements; and

an adjustment transistor ~~for setting~~that sets a control terminal of the driving transistor to a predetermined potential prior to the transfer of the data signal to the holding element.

18. (Currently Amended) ~~An~~The electro-optical device according to Claim 17, ~~characterized in that~~ each of the plurality of unit circuits comprises a second switching transistor ~~for controlling~~that controls the electronic connection or the electronic disconnection between the adjustment transistor and the predetermined potential.

19. (Currently Amended) ~~An~~The electro-optical device according to Claim 17, ~~characterized in that~~ the electro-optical elements ~~are~~being organic EL elements.

20. (Currently Amended) A driving method for an electro-optical device comprising a plurality of scanning lines, a plurality of data lines, a plurality of power lines, and a plurality of unit circuits ~~comprising~~including:

a first transistor ~~including~~having a first terminal, a second terminal, and a first control terminal;

a second transistor ~~including~~having a third terminal and a fourth terminal, the third terminal being ~~connected~~coupled to the first control terminal; and

a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~coupled to the first control terminal,

the driving method ~~characterized by~~ comprising:

~~a first step of electronically connecting~~coupling the fourth terminal to a predetermined potential and of setting the first control terminal to a first potential; and

~~a second step of,~~ after a scanning signal is sent through the plurality of scanning lines to a third transistor of which one end is ~~connected~~coupled to the second electrode to turn on the third transistor, and when the fourth terminal is electronically disconnected from the predetermined potential, applying the voltage corresponding to a data signal from the plurality of data lines to the second electrode through the third transistor to change the potential of the second electrode from a second potential to a third potential to change the potential of the first control terminal from the first potential.

21. (Currently Amended) ~~A~~The driving method for the electro-optical device according to Claim 20,

~~characterized in that~~ the potential of the second electrode of the capacitive element ~~is being~~ set to the second potential while at least the ~~first step~~coupling of the fourth terminal to a predetermined potential is being performed.

22. (Currently Amended) ~~An~~The electronic ~~apparatus~~apparatus ~~characterized by~~ having mounted thereon an electronic circuit according to Claim 1.


23. (Currently Amended) ~~An~~The electronic ~~apparatus~~apparatus ~~characterized by~~ having mounted thereon an electro-optical device according to Claim 15.

REMARKS

Claims 1-23 are pending in this application. By this Preliminary Amendment, the Abstract and specification are replaced with an amended Abstract and substitute specification, and claims 1-23 are amended. No new matter is added.

Prompt and favorable examination on the merits is respectfully requested.

Respectfully submitted,



James A. Oliff
Registration No. 27,075

John S. Kern
Registration No. 42,719

JAO:JSK/kap

Date: September 15, 2003

OLIFF & BERRIDGE, PLC
P.O. Box 19928
Alexandria, Virginia 22320
Telephone: (703) 836-6400

<p>DEPOSIT ACCOUNT USE AUTHORIZATION Please grant any extension necessary for entry; Charge any fee due to our Deposit Account No. 15-0461</p>

ABSTRACT OF THE DISCLOSURE

~~To provide~~The invention provides an electronic circuit, a driving method for an electronic circuit, an electro-optical device, a driving method for an electro-optical device, and an electronic ~~apparatus~~apparatus which can reduce the dispersion of the threshold voltages of transistors. A driving transistor ~~Trd~~, first and second switching transistors ~~Tr1 and Tr2~~, an adjustment transistor ~~Tre~~, a coupling capacitor ~~C1~~, and a holding capacitor ~~C2~~ form a pixel circuit-20. The threshold voltage of the adjustment transistor ~~Tre~~ is applied to the gate of the driving transistor ~~Trd~~. According to the present invention, the luminance gradation of a display element, such as an organic EL element, can be precisely controlled according to a data voltage.

SYSTEM AND METHODS FOR DRIVING AN

~~ELECTRONIC CIRCUIT, DRIVING METHOD FOR ELECTRONIC CIRCUIT,
ELECTRO-OPTICAL DEVICE, DRIVING METHOD FOR ELECTRO-OPTICAL
DEVICE, AND ELECTRONIC APPARATUS.~~

BACKGROUND OF THE INVENTION

1. Field of Invention

[0001] The present invention relates to electronic circuits, driving methods for electronic circuits, electro-optical devices, driving methods for electro-optical devices, and electronic apparatus.

2. Description of Related Art

[0002] An active-matrix driving method is one of driving methods for electro-optical ~~devices~~ having electro-optical elements, such as liquid-crystal elements, organic EL elements, electro-phoresis elements, and electron-emission elements. In electro-optical ~~devices~~ which use the active-matrix driving method, a plurality of pixel circuits are disposed in a matrix manner in a display panel section. Each of the plurality of pixel circuits ~~is~~ *include* including an electro-optical element and a driving transistor for supplying driving power to the electro-optical element. *as described in,*

[0003] Among those elements, since current-driven elements ~~(patent reference 1)~~ driven by current, such as organic EL elements, have luminance which depends on the current level, it is necessary to drive their pixel circuits precisely. ~~(patent reference 1)~~

Patent reference 1
Pamphlet of International Publication No. WO98/36407

[0004] Since the plurality of pixel circuits have dispersion in characteristics, such as the threshold voltages of the driving transistors, even when data signals corresponding to the same gradation are sent, the luminance of the electro-optical elements differs at the plurality of pixels. Especially when thin-film transistors are used as the driving transistors, a desired display quality may not be obtained because the thin-film transistors have much dispersion in their threshold voltages.

[0005] The present invention has been made to solve the above-described problem. An object of the present invention is to provide an electronic circuit, a driving method for an electronic circuit, an electro-optical device, a driving method for an electro-optical device, and an electronic apparatus which can reduce dispersion in the threshold voltages of transistors. *at least*

SUMMARY OF THE INVENTION

[0006] An electronic circuit according to the present invention includes *can* a first transistor including a first terminal, a second terminal, and a first control terminal, a second

transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being connected to the first control terminal, a capacitive element including a first electrode and a second electrode, the first electrode being connected to the first control terminal, and a third transistor including a fifth terminal and a sixth terminal, the fifth terminal being connected to the second electrode, and the second control terminal is connected to the third terminal.

[0007] With this, the electronic circuit compensates the threshold voltage of the first transistor for a change caused by manufacturing dispersion.

[0008] This electronic circuit includes a fourth transistor including a seventh terminal and an eighth terminal, the seventh terminal being connected to the fourth terminal of the second transistor.

[0009] With this, the conduction state of the fourth transistor can be controlled to set the potential of the first control terminal to a desired potential and to maintain it.

[0010] In the electronic circuit, the first terminal may be connected to an electronic element.

[0011] In the electronic circuit, the electronic element may be, for example, a current-driven element.

[0012] An electronic circuit according to the present invention includes a plurality of first signal lines, a plurality of second signal lines, a plurality of power lines, and a plurality of unit circuits. Each of the plurality of unit circuits includes a first transistor including a first terminal, a second terminal, and a first control terminal, a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being connected to the first control terminal, a capacitive element including a first electrode and a second electrode, the first electrode being connected to the first control terminal, and a third transistor including a fifth terminal, a sixth terminal, and a third control terminal, the fifth terminal being connected to the second electrode, the second control terminal is connected to the third terminal, and the third control terminal is connected to one of the plurality of first signal lines.

[0013] With this, the electronic circuit compensates the threshold voltage of the first transistor for a change caused by manufacturing dispersion.

[0014] The electronic circuit includes a fourth transistor including a seventh terminal, an eighth terminal, and a fourth control terminal, the seventh terminal being connected to the fourth terminal, and the fourth control terminal being connected to one of the plurality of second signal lines.

[0015] With this, the conduction state of the fourth transistor can be controlled to set the potential of the first control terminal to a desired potential and to maintain it.

[0016] In the electronic circuit, the first terminal may be connected to an electronic element.

[0017] In the electronic circuit, the electronic element may be, for example, a current-driven element.

[0018] An electronic circuit according to the present invention includes ^{can} a holding element for holding a signal as a charge; a first switching transistor for controlling the transfer of the signal to the holding element; a driving transistor of which the conduction state is set according to the charge held by the holding element; and an adjustment transistor for setting a control terminal of the driving transistor to a predetermined potential prior to the transfer of the signal to the holding element.

[0019] With this, the electronic circuit can compensate the threshold voltage of the driving transistor by on/off control of the first switching transistor.

[0020] It is preferred that the electronic circuit include a second switching transistor for controlling the electronic connection or the electronic disconnection between the adjustment transistor and the predetermined potential.

[0021] In the electronic circuit, the driving transistor may be connected to an electronic element.

[0022] In the electronic circuit, the electronic element may be, for example, a current-driven element.

[0023] A driving method for an electronic circuit according to the present invention is a driving method for an electronic circuit which includes a first transistor including a first terminal, a second terminal, and a first control terminal, a second transistor including a third terminal and a fourth terminal, the third terminal being connected to the first control terminal, and a capacitive element including a first electrode and a second electrode, the first electrode being connected to the first control terminal, and the driving method includes a first step of electronically connecting the fourth terminal to a predetermined potential and of setting the first control terminal to a first potential, and a second step of, when the fourth terminal is electronically disconnected from the predetermined potential, changing the potential of the second electrode of the capacitive element from a second potential to a third potential to change the potential of the first control terminal from the first potential.

[0024] With this, the electronic circuit which compensates the threshold voltage of the first transistor for a change caused by manufacturing dispersion is driven.

[0025] It is preferred in the driving method for the electronic circuit that the first step be performed when the potential of the second electrode is set to the second potential.

[0026] An electro-optical device according to the present invention, includes ^{can} a plurality of scanning lines, a plurality of data lines, a plurality of power lines, and a plurality of unit circuits having electro-optical elements, each of the plurality of unit circuits includes a first transistor including a first terminal, a second terminal, and a first control terminal; an electro-optical element connected to the first terminal ^{can} a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being connected to the first control terminal ^{can} a capacitive element including a first electrode and a second electrode, the first electrode being connected to the first control terminal ^{can} a third transistor including a fifth terminal, a sixth terminal, and a third control terminal, the fifth terminal being connected to the second electrode; and a fourth transistor including a seventh terminal and an eighth terminal, the seventh terminal being connected to the fourth terminal, the second control terminal is connected to the third terminal, the third control terminal is connected to one of the plurality of scanning lines, and the sixth terminal is connected to one of the plurality of data lines.

[0027] With this, the threshold voltage of the first transistor is compensated for a change caused by manufacturing dispersion. As a result, since the luminance gradations of the electro-optical elements can be precisely controlled, the display quality of the electro-optical device can be improved as compared with a conventional electro-optical device.

[0028] In the electro-optical device, the electro-optical elements may be, for example, organic EL elements.

[0029] An electro-optical device according to the present invention, includes ^{can} a plurality of scanning lines, a plurality of data lines, a plurality of power lines, and a plurality of unit circuits having electro-optical elements ^{can} each of the plurality of unit circuits includes ^{can} a first switching transistor of which the conduction state is controlled according to a scanning signal sent through one corresponding scanning line of the plurality of scanning lines ^{can} a holding element for accumulating a data signal sent through one data line of the plurality of data lines and the first switching transistor, as a charge ^{can} a driving transistor of which the conduction state is set according to the amount of the charge accumulated by the holding element, for supplying current having a current level according to the conduction state to the electro-optical elements ^{can} and an adjustment transistor for setting a control terminal of the driving transistor to a predetermined potential prior to the transfer of the data signal to the holding element. *The device can further include*

[0030] With this, the threshold voltage of the driving transistor is compensated for a change caused by manufacturing dispersion. As a result, since the luminance gradations of the electro-optical elements can be precisely controlled, the display quality of the electro-optical device can be improved as compared with a conventional electro-optical device.

[0031] In the electro-optical device, each of the plurality of unit circuits includes a second switching transistor for controlling the electronic connection or the electronic disconnection between the adjustment transistor and the predetermined potential.

[0032] With this, the threshold voltage of the first transistor can be compensated by on/off control of the second switching transistor.

[0033] In the electro-optical device, the electro-optical elements are, for example, organic EL elements.

[0034] A driving method for an electro-optical device according to the present invention is a driving method for an electro-optical device which includes a plurality of scanning lines, a plurality of data lines, a plurality of power lines, and a plurality of unit circuits including a first transistor including a first terminal, a second terminal, and a first control terminal, a second transistor including a third terminal and a fourth terminal, the third terminal being connected to the first control terminal, and a capacitive element including a first electrode and a second electrode, the first electrode being connected to the first control terminal, and the driving method includes a first step of electronically connecting the fourth terminal to a predetermined potential and of setting the first control terminal to a first potential, and a second step of, after a scanning signal is sent through the plurality of scanning lines to a third transistor of which one end is connected to the second electrode to turn on the third transistor, and when the fourth terminal is electronically disconnected from the predetermined potential, applying the voltage corresponding to a data signal from the plurality of data lines to the second electrode through the third transistor to change the potential of the second electrode from a second potential to a third potential to change the potential of the first control terminal from the first potential.

[0035] With this, the electro-optical device which compensates the threshold voltage of the first transistor can be driven.

[0036] The potential of the second electrode of the capacitive element is set to the second potential while at least the first step is being performed.

[0037] In the driving method for the electro-optical device, it is preferred that the first step be performed when the potential of the second electrode of the capacitive element is set to the second potential.

[0038] An electronic apparatus according to the present invention is characterized by having mounted thereon the electronic circuit.

[0039] Since the electronic apparatus is including the electronic circuit, precise current control can be performed.

[0040] A second electronic apparatus according to the present invention is characterized by having mounted thereon the electro-optical device.

[0041] With this, the electronic apparatus has a good-display-quality display unit.

BRIEF DESCRIPTION OF THE DRAWINGS

[0042] Fig. 1 is a block circuit diagram showing the circuit structure of an organic EL display according to a first embodiment;

[0043] Fig. 2 is a block circuit diagram showing the internal circuit structure of a display panel section and a data-line driving circuit;

[0044] Fig. 3 is a circuit diagram of a pixel circuit according to the first embodiment;

[0045] Fig. 4 is a timing chart showing the operation of the pixel circuit according to the first embodiment;

[0046] Fig. 5 is a perspective view showing the structure of a mobile personal computer used for describing a second embodiment; and

[0047] Fig. 6 is a perspective view showing the structure of a mobile telephone used for describing the second embodiment.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

(First embodiment)

[0048] An organic EL display will be taken as an example of an electro-optical device according to an embodiment of the present invention and described by referring to Fig. 1 to Fig. 4. Fig. 1 shows the structure of the control block of the organic EL display. Fig. 2 is a block circuit diagram showing the internal circuit structure of a display panel section and a data-line driving circuit. Fig. 3 is a circuit diagram of a pixel circuit. Fig. 4 is a timing chart showing a driving method for the pixel circuit.

[0049] As shown in Fig. 1, the organic EL display 10 is including a control circuit 11, the display panel section 12, a scanning-line driving circuit 13, and the data-line driving circuit 14.

[0050] The control circuit 11, the scanning-line driving circuit 13, and the data-line driving circuit 14 of the organic EL display 10 may be structured by independent electronic components. For example, each of the control circuit 11, the scanning-line driving circuit 13,

The invention will be described with reference to the above embodiments, wherein like numerals reference like elements, and wherein:

and the data-line driving circuit 14 may be structured by a one-chip semiconductor integrated-circuit device. The whole or a part of the control circuit 11, the scanning-line driving circuit 13, and the data-line driving circuit 14 may be structured by a programmable IC chip where their functions are implemented by a program written into the IC chip in a software manner.

[0051] The control circuit 11 generates a scanning control signal and a data control signal both used for displaying an image on the display panel section 12 according to the image data sent from an external device not shown. The control circuit 11 outputs the scanning control signal to the scanning-line driving circuit 13, and outputs the data control signal to the data-line control circuit 14.

[0052] As shown in Fig. 2, the display panel section 12 has a plurality of pixel circuits 20 serving as electronic circuits or unit circuits, disposed at the positions corresponding to the intersections of M data lines X_m ($m = 1-M$, m is an integer) extending in a column direction and N scanning lines Y_n ($n = 1-N$, n is an integer) extending in a row direction. In other words, the plurality of pixel circuits 20 are connected to the data lines X_m extending in the column direction and the scanning lines Y_n extending in the row direction, and are arranged in a matrix manner. Each scanning line Y_n is formed of a first sub-scanning line Y_{s1} and a second sub-scanning line Y_{s2} (see Fig. 3), described later.

[0053] The pixel circuit 20 has an organic EL element 21 serving as an electronic element or electro-optical element, as shown in Fig. 2. The pixel circuit 20 is also connected to a power line VL extending in the column direction, and a driving voltage V_{dd} serving as a power potential is sent to the pixel circuit 20 through the power line VL. In the present invention, a transistor, described later, disposed in the pixel circuit 20 ~~is~~ ^{can be} a thin-film transistor (TFT). The transistor is not limited to a TFT. It may be, for example, a MOS transistor.

[0054] The scanning-line driving circuit 13 selects one scanning line from the plurality of scanning lines Y_n disposed in the display panel section 12, according to the scanning control signal output from the control circuit 11, and outputs a scanning signal to the selected scanning line.

[0055] The data-line driving circuit 14 ~~is including~~ ^{can include} a plurality of single-line drivers 23, as shown in Fig. 2. The single-line drivers 23 are connected to the data lines X_m disposed in the display panel section 12.

[0056] More specifically, the data-line driving circuit 14 generates a data voltage V_{data} serving as a data signal according to the data control signal output from the control circuit 11. The generated data voltage V_{data} is sent to the pixel circuits 20 through the data

lines Xm. The internal states of the pixel circuits 20 are set according to the data voltage Vdata to control driving current Iel (see Fig. 3) flowing into the organic EL elements 21. The data-line driving circuit 14 also sends a driving voltage Vdd to the pixel circuits 20 in a data writing period T1, described later, before the data voltage Vdata.

[0057] The pixel circuits 20 constituting the organic EL display 10 structured in this way will be described by referring to Fig. 3.

[0058] The pixel circuit 20 is including a driving transistor Trd and an adjustment transistor Trc, as shown in Fig. 3. The pixel circuit 20 is also including a first switching transistor Tr1 and a second switching transistor Tr2. The pixel circuit 20 is further including a coupling capacitor C1 and a holding capacitor C2 serving as capacitive elements or holding element.

[0059] The first transistor and the driving transistor, the first terminal, the second terminal, and the first control terminal and the control terminal described in Claims correspond, in the present embodiment, to the driving transistor Trd, the drain of the driving transistor Trd, and the source of the driving transistor Trd, and the gate of the driving transistor Trd. The second transistor and the adjustment transistor, the third terminal, the fourth terminal, and the second control terminal and the control terminal correspond to the adjustment transistor Trc, the drain of the adjustment transistor, the source of the adjustment transistor Trc, and the gate of the adjustment transistor Trc. Further, the third transistor, the fifth terminal, the sixth terminal, and the third control terminal correspond to the first switching transistor Tr1, the drain of the first switching transistor Tr1, the source of the first switching transistor Tr1, and the gate of the first switching transistor Tr1. The fourth transistor, the seventh terminal, the eighth terminal, and the fourth control terminal correspond to the second switching transistor Tr2, the source of the second switching transistor Tr2, the drain of the second switching transistor Tr2, and the gate of the second switching transistor Tr2.

[0060] The driving transistor Trd and the adjustment transistor Trc have p-type (p-channel) conductivity. The first and second switching transistors Tr1 and Tr2 have n-type (n-channel) conductivity.

[0061] The drain of the driving transistor Trd is connected to the anode of the organic EL element 21. The cathode of the organic EL element is grounded. The source of the driving transistor Trd is connected to the power line VL. The gate of the driving transistor Trd is connected to the coupling capacitor C1, the holding capacitor C2, and the

adjustment transistor Trc. The coupling capacitor C1 has a capacitance of Ca, and the holding capacitor C2 has a capacitance of Cb.

[0062] More specifically, a first electrode La of the coupling capacitor C1 is connected to the gate of the driving transistor Trd, and a second electrode Lb thereof is connected to the drain of the first switching transistor Tr1. A third electrode Lc of the holding capacitor C2 is connected to the gate of the driving transistor Trd, and a fourth electrode Ld thereof is connected to the power line VL.

[0063] The gate of the first switching transistor Tr1 is connected to the first sub-scanning line Ys1 serving as a first signal line constituting the scanning line Yn.

[0064] The gate of the adjustment transistor Trc is connected to the drain thereof, and also connected to the gate of the driving transistor Trd at a node N. The source of the adjustment transistor Trc is connected to the source of the second switching transistor Tr2. The drain of the second switching transistor Tr2 is connected to the power line VL, and the gate thereof is connected to the second sub-scanning line Ys2 serving as a second signal line constituting the scanning line Yn. The first sub-scanning line Ys1 and the second sub-scanning line Ys2 constitute the scanning line Yn.

[0065] The threshold voltage Vth2 of the adjustment transistor Trc is set so as to be almost the same as the threshold voltage Vth1 of the driving transistor Trd. The threshold voltage Vth2 of the adjustment transistor Trc may be set appropriately according to its driving condition. The driving voltage Vdd is set in advance so as to be sufficiently higher than the data voltage Vdata.

[0066] The operation of the pixel circuits 20 in the organic EL display 10, structured as described above, will be described next by referring to Fig. 4. In Fig. 4, Tc, T1, and T2 indicate, respectively, a driving period, a data writing period serving as a first step, and a light-emitting period serving as a second step. The driving period Tc is formed of the data writing period T1 and the light-emitting period T2. The driving period Tc indicates a period in which the luminance gradation of the organic EL element 21 is updated once, and is equal to a so-called frame period.

[0067] In the data writing period T1, a second scanning signal SC2 for turning on the second switching transistor Tr2 is first applied from the scanning-line driving circuit 13 to the gate of the second switching transistor Tr2 through the second sub-scanning line Ys2. Then, the second switching transistor Tr2 is turned on. As a result, the driving voltage Vdd is sent to the source of the adjustment transistor Trc through the power line VL. At this time, a first scanning signal SC1 for turning off the first switching transistor Tr1 is applied from the

scanning-line driving circuit 13 to the gate of the first switching transistor Tr1 through the first sub-scanning line Ys1.

[0068] With this, the potential of the source of the adjustment transistor Trc becomes equal to the driving voltage Vdd. A potential Vn1 obtained at the node N is equal to the value ($Vn1 = Vdd - Vth2$) obtained by subtracting the threshold voltage Vth2 of the adjustment transistor Trc from the driving voltage Vdd, and the potential Vn1 is held by the holding capacitor C2 as an initial potential Vc1. The potential Vn1 is also sent to the gate of the driving transistor Trd. As a result, since the threshold voltage Vth2 of the adjustment transistor Trc is almost the same as the threshold voltage Vth1 of the driving transistor Trd, as described before, the threshold voltage Vth1 of the driving transistor Trd is compensated.

[0069] Then, the second scanning signal SC2 for turning off the second switching transistor Tr2 is applied from the scanning-line driving circuit 13 to the gate of the second switching transistor Tr2 through the second sub-scanning line Ys2. The second switching transistor Tr2 is turned off. Next, the first scanning signal SC1 for turning on the first switching transistor Tr1 is applied from the scanning-line driving circuit 13 to the gate of the first switching transistor Tr1 through the first sub-scanning line Ys1. The first switching transistor Tr1 is turned on.

[0070] The driving voltage Vdd is sent to the pixel circuit 20 through the data line Xm. Then, immediately, the data voltage Vdata is sent from the single-line driver 23 of the data-line driving circuit 14 through the data line Xm.

[0071] With this, the initial potential Vc1 is changed to the value indicated by the following expression with the use of the capacitance Ca of the coupling capacitor C1 and the capacitance Cb of the holding capacitor C2.

$$Vc1 = Vdd - Vth2 + Ca/(Ca + Cb) \cdot \Delta Vdata$$

[0072] $\Delta Vdata$ indicates the potential difference ($= Vdd - Vdata$) between the driving voltage Vdd and the data voltage Vdata. And, this value, $Vdd - Vth2 + Ca/(Ca + Cb) \cdot \Delta Vdata$, is sent to the gate of the driving transistor Trd as the final potential Vc2.

[0073] The conduction state of the driving transistor Trd is determined according to the final potential Vc2, and the driving current Iel determined according to the conduction state flows into the organic EL element 21. The current Iel is determined by the following equation when Vgs indicates the voltage difference between the gate voltage and the source voltage of the driving transistor Trd.

$$Iel = (1/2)\beta(-Vgs - Vth1)^2$$

[0074] In the equation, β indicates a gain coefficient. The gain coefficient β is obtained by $\beta = (\mu AW/L)$, where μ indicates carrier mobility, A indicates a gate capacitance, W indicates a channel width, and L indicate a channel length. The gate voltage V_g of the driving transistor Trd is equal to the final potential V_{c2} . In other words, the voltage difference V_{gs} between the gate voltage and the source voltage of the driving transistor Trd can be expressed by the following equation.

$$V_{gs} = V_{dd} - [V_{dd} - V_{th2} + C_a/(C_a + C_b) \cdot \Delta V_{data}]$$

[0075] Therefore, the driving current I_{el} of the driving transistor Trd is expressed by the following equation.

$$I_{el} = (1/2)\beta[V_{th2} - C_a/(C_a + C_b) \cdot \Delta V_{data} - V_{th1}]^2$$

[0076] In the equation, since the threshold voltage V_{th2} of the adjustment transistor Trc is set, as described before, to be almost the same as the threshold voltage V_{th1} of the driving transistor Trd, the driving current I_{el} can be expressed by the following equation.

$$\begin{aligned} I_{el} &= (1/2)\beta[V_{th2} - C_a/(C_a + C_b) \cdot \Delta V_{data} - V_{th1}]^2 \\ &= (1/2)\beta[C_a/(C_a + C_b) \cdot \Delta V_{data}]^2 \end{aligned}$$

Therefore, as indicated by the above equation, the driving current I_{el} does not depend on the threshold voltage V_{th1} of the driving transistor Trd, and has the magnitude corresponding to the data voltage V_{data} . This driving current I_{el} flows into the organic EL element 21, and the organic EL element 21 emits light.

[0077] Next, after the data writing period T1 is finished, the first scanning signal SC1 for turning off the first switching transistor Tr1 is applied from the scanning-line driving circuit 13 to the gate of the first switching transistor Tr1 through the first sub-scanning line Ys1 in the light-emitting period T2. The first switching transistor Tr1 is turned off.

[0078] In this light-emitting period T2, the driving current I_{el} corresponding to the conduction state of the driving transistor Trd, determined correspondingly to the final potential V_{c2} is sent to the organic EL element 21.

[0079] With the above conditions, even if the threshold voltage V_{th1} of the driving transistor Trd in each pixel circuit 20 differs due to dispersion in manufacturing, the driving current I_{el} is determined only by the data voltage V_{data} . Therefore, the luminance gradation of the organic EL element 21 is precisely controlled according to the data voltage V_{data} . As a result, the organic EL display 10 has a good display quality.

[0080] The following advantage is obtained with the organic EL display 10 and the pixel circuits 20 according to the present embodiment.

[0081] ~~(X)~~ In the present embodiment, the pixel circuit 20 ~~is~~ ^{can be} formed of the driving transistor Trd, the first and second switching transistors Tr1 and Tr2, the adjustment transistor Trc, the coupling capacitor C1, and the holding capacitor C2. The threshold voltage Vth2 of the adjustment transistor Trc, for generating the compensation voltage for compensating for the threshold voltage Vth1 of the driving transistor Trd is applied to the gate of the driving transistor Trd. With this, the threshold voltage Vth2 of the driving transistor Trd is compensated. Therefore, since the dispersion of the threshold voltages Vth1 of the driving transistors Trd in the pixel circuits 20 can be reduced, the driving current Iel corresponding to the data voltage Vdata sent from the data-line driving circuit 14 through the data lines Xm can be precisely controlled. Therefore, the luminance graduation of the organic EL elements 21 can be precisely controlled according to the data voltage Vdata. As a result, the organic EL display 10 has a good display quality.

[0082] In the above embodiment, the driving transistor Trd, the first and second switching transistors Tr1 and Tr2, and the adjustment transistor Trc are a p-type transistor, an n-type transistor, an n-type transistor, and a p-type transistor, respectively. ^{However, it should be understood that} Their conductivity types are not limited to this case. Any conductivity-type transistors can be used if appropriate. For example, n-type transistors can be used as the driving transistor Trd and the adjustment transistor Trc. Transistors having different conductivity types can be used as the first and second switching transistors Tr1 and Tr2. In this case, when the gates of the first and second switching transistors Tr1 and Tr2 are connected to a common signal line, such as a scanning line, and are operated complementarily, an area required for wiring can also be reduced.

~~~~~ (Second embodiment)

[0083] Applications of the organic EL display 10 serving as an electro-optical device, described in the first embodiment, to electronic apparatus ~~will~~ ^X be described by referring to Fig. 5 and Fig. 6. The organic EL display 10 can be applied to various electronic apparatus, such as mobile personal computers, portable telephones, and digital cameras.

[0084] Fig. 5 is a perspective view showing the structure of a mobile personal computer. In Fig. 5, the personal computer 50 is including a body section 52 having a keyboard 51, and a display unit 53 which uses the organic EL display 10. Also in this case, the display unit 53, which uses the organic EL display 10, has the same advantage as in the first embodiment. As a result, the mobile personal computer 50 has a good display quality with the organic EL display 10.

[0085] Fig. 6 is a perspective view of showing the structure of a portable telephone. In Fig. 6, the portable telephone 60 is including a plurality of operation buttons 61, a receiver 62, a transmitter 63, and a display unit 64 which uses the organic EL display 10. Also in this case, the display unit 64, which uses the organic EL display 10, has the same advantage as in the first embodiment. As a result, the portable telephone 60 has a good display quality with the organic EL display 10. *It should be understood that*

[0086] *The* present invention is not limited to the above embodiments. Various embodiments can be possible such as those described below.

[0087] In the above embodiments, the present invention is embodied in a pixel circuit having an organic EL element, serving as a unit circuit. The present invention may be embodied in a unit circuit which drives one of various electro-optical elements, such as liquid-crystal elements, electro-phoresis elements, electron-emission elements, inorganic EL elements, LEDs, and FEDs. The present invention may be embodied in storage devices such as RAMs.

[0088] In the above embodiments, the organic EL displays have pixel circuits equipped with one-color organic EL elements. The present invention can also be applied to an EL display in which organic EL elements which emit light of three colors, red, green, and blue, or more colors are provided for pixel circuits for the colors.

ADD

While this invention has been described in conjunction with specific embodiments thereof, it is evident that many alternatives, modifications, and variations will be apparent to those skilled in the art. Accordingly, preferred embodiments of the invention as set forth herein are intended to be illustrative, not limiting. Various changes may be made without departing from the spirit and scope of the invention.

Amend CLAIMS by Prelim

14

WHAT IS CLAIMED IS:

1. An electronic circuit ~~characterized by~~ comprising:
a first transistor including a first terminal, a second terminal, and a first control terminal;
a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being ~~connected~~ ^{Coupled} to the first control terminal;
a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~ ^{coupled} to the first control terminal; and
a third transistor including a fifth terminal and a sixth terminal, the fifth terminal being ~~connected~~ ^{Coupled} to the second electrode, the second control terminal being ~~connected~~ ^{Coupled} to the third terminal.

^{The} 2. An electronic circuit according to Claim 1, ^{coupled} further comprising a fourth transistor including a seventh terminal and an eighth terminal, the seventh terminal being ~~connected~~ ^{coupled} to the fourth terminal.

^{The} 3. ~~An~~ electronic circuit according to Claim 1, ^{coupled} the first terminal being ~~connected~~ ^{Coupled} to an electronic element.

^{The} 4. ~~An~~ electronic circuit according to Claim 3, the electronic element being a current-driven element.

^{Start} 5. ~~An~~ electronic circuit ^{further} comprising:
a plurality of first signal lines;
a plurality of power lines; and
a plurality of unit circuits, each of the plurality of unit circuits comprising:
a first transistor including a first terminal, a second terminal, and a first control terminal;
a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being ~~connected~~ ^{coupled} to the first control terminal;
a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~ ^{coupled} to the first control terminal; and
a third transistor including a fifth terminal, a sixth terminal, and a third control terminal, the fifth terminal being ~~connected~~ ^{coupled} to the second electrode, the second control terminal being ~~connected~~ ^{coupled} to the third terminal, and the third control terminal being ~~connected~~ ^{coupled} to a respective first signal line of the plurality of first signal lines.

^{The} 6. ~~An~~ electronic circuit according to Claim 5,

further comprising a plurality of second signal lines,
 each of the plurality of unit circuits further comprising a fourth transistor
 including a seventh terminal, an eighth terminal, and a fourth control terminal,
 the seventh terminal being ~~connected~~ to the fourth terminal, and
 the fourth control terminal being ~~connected~~ to a respective second signal line
 of the plurality of second signal lines.

7. ~~An~~ electronic circuit according to Claim 5,
 the first terminal being ~~connected~~ to an electronic element.

8. ~~An~~ electronic circuit according to Claim 7,
 the electronic element being a current-driven element.

9. ~~An~~ electronic circuit comprising:
 a holding element ~~for holding~~ a signal as a charge;
 a first switching transistor ~~for controlling~~ the transfer of the signal to the
 holding element;
 a driving transistor of which the conduction state is set according to the charge
 held by the holding element; and
 an adjustment transistor ~~for setting~~ a control terminal of the driving transistor
 to a predetermined potential prior to the transfer of the signal to the holding element.

10. ~~An~~ electronic circuit according to Claim 9,
 further comprising a second switching transistor ~~for controlling~~ the electronic
 connection or the electronic disconnection between the adjustment transistor and the
 predetermined potential.

11. ~~An~~ electronic circuit according to Claim 9,
 the driving transistor being ~~connected~~ to an electronic element.

12. ~~An~~ electronic circuit according to Claim 11,
 the electronic element being a current-driven element.

13. A driving method for an electronic circuit comprising:
 a first transistor including a first terminal, a second terminal, and a first control
 terminal;
 a second transistor including a third terminal and a fourth terminal, the third
 terminal being ~~connected~~ to the first control terminal; and
 a capacitive element including a first electrode and a second electrode, the first
 electrode being ~~connected~~ to the first control terminal,
 the driving method comprising:

~~a first step of~~ electronically connecting the fourth terminal to a predetermined potential for setting the first control terminal to a first potential; and

~~a second step of~~ when the fourth terminal is electronically disconnected from the predetermined potential, changing the potential of the second electrode of the capacitive element from a second potential to a third potential to change the potential of the first control terminal from the first potential.

14. ~~A~~ ^{The} driving method for the electronic circuit according to Claim 13, the potential of the second electrode being set to the second potential while at least the ~~first step~~ is being performed.

15. An electro-optical device comprising:

a plurality of scanning lines;

a plurality of data lines;

a plurality of power lines; and

a plurality of unit circuits having electro-optical elements,

^{Further} ~~the electro-optical device characterized in that~~ each of the plurality of unit circuits comprises: ~~(X)~~ ^{Start}

a first transistor including a first terminal, a second terminal, and a first control terminal;

an electro-optical element ^{coupled} ~~connected~~ to the first terminal;

a second transistor including a third terminal, a fourth terminal, and a second control terminal, the third terminal being ~~connected~~ ^{coupled} to the first control terminal;

a capacitive element including a first electrode and a second electrode, the first electrode being ~~connected~~ ^{coupled} to the first control terminal;

a third transistor including a fifth terminal, a sixth terminal, and a third control terminal, the fifth terminal being ~~connected~~ ^{coupled} to the second electrode; and

^{Coupled} a fourth transistor including a seventh terminal and an eighth terminal, the seventh terminal being ~~connected~~ ^{coupled} to the fourth terminal,

the second control terminal is ~~connected~~ ^{coupled} to the third terminal,

the third control terminal is ~~connected~~ ^{coupled} to one of the plurality of scanning lines,

and

^{coupled} the sixth terminal is ~~connected~~ ^{coupled} to one of the plurality of data lines.

16. ~~An~~ ^{The} electro-optical device according to Claim 15,

~~characterized in that~~ the electro-optical element ~~is~~ ^{being} an organic EL element.

17. An electro-optical device comprising a plurality of scanning lines, a plurality of data lines, a plurality of power lines, and a plurality of unit circuits having electro-optical elements,

~~the electro-optical device characterized in that~~ each of the plurality of unit circuits comprises:

a first switching transistor of which the conduction state is controlled according to a scanning signal sent through one corresponding scanning line of the plurality of scanning lines;

a holding element *that accumulates* for accumulating a data signal sent through one data line of the plurality of data lines and the first switching transistor, as a charge;

a a driving transistor of which the continuity state is set according to the amount of the charge accumulated by the holding element, *that supplies* for supplying current having a current level according to the conduction state to the electro-optical elements; and

an adjustment transistor *that sets* for setting a control terminal of the driving transistor to a predetermined potential prior to the transfer of the data signal to the holding element.

18. ~~An electro-optical device according to Claim 17,~~
The ~~characterized in that~~ each of the plurality of unit circuits comprises a second switching transistor *that controls* for controlling the electronic connection or the electronic disconnection between the adjustment transistor and the predetermined potential.

19. ~~An electro-optical device according to Claim 17,~~
The ~~characterized in that~~ the electro-optical elements *being* are organic EL elements.

20. A driving method for an electro-optical device comprising a plurality of scanning lines, a plurality of data lines, a plurality of power lines, and a plurality of unit circuits ~~comprising:~~ *including*

a first transistor *including* a first terminal, a second terminal, and a first control terminal;

coupled a second transistor *having* including a third terminal and a fourth terminal, the third terminal *having* being connected to the first control terminal; and

a capacitive element including a first electrode and a second electrode, the first electrode being *coupled* connected to the first control terminal,

the driving method ~~characterized by~~ comprising:

~~a first step of electronically connecting the fourth terminal to a predetermined potential and of setting the first control terminal to a first potential; and~~

coupling

~~a second step of~~ after a scanning signal is sent through the plurality of scanning lines to a third transistor of which one end is ~~connected~~ ^{coupled} to the second electrode to turn on the third transistor, and when the fourth terminal is electronically disconnected from the predetermined potential, applying the voltage corresponding to a data signal from the plurality of data lines to the second electrode through the third transistor to change the potential of the second electrode from a second potential to a third potential to change the potential of the first control terminal from the first potential.

21. ~~The~~ driving method for the electro-optical device according to Claim 20, ^{being} ~~characterized in that~~ the potential of the second electrode of the capacitive element is set to the second potential while at least the ~~first step~~ is being performed.
22. ~~An electronic apparatus characterized by~~ ^{The} having mounted thereon an electronic circuit according to Claim 1.
23. ~~An electronic apparatus characterized by~~ ^{The} having mounted thereon an electro-optical device according to Claim 15.

Coupling of the fourth terminal
to a predetermined potential